

	BOQ FOR ELECTRICAL WORKS AT: SECTOR 55 BRANCH, CAN	ARA BAN			
S. NO.	DESCRIPTION OF ITEM	QTY	ИОМ	RATE (Rs.) (Excl. GST)	AMOUNT (Rs.) (Excl. GST)
1	SITC of 3 Nos. 100 Amp. Kit-kat Fuse unit along with 100 Amp. neutral link	1.00	Set		
-	on wooden board of size 2'0" X 2'0" complete with connections complete in				
	all respect to the satisfaction of Bank.				
2	ELECTRICAL PANEL	1.00	No.		
	Design, manufacture, providing, storing & installing in position, effecting				
	proper connection, testing and commissioning of panel made of 16 SWG,				
	CRCA sheet steel. It shall be dust and vermin proof. It shall have				
	compartmentalized construction with bus bar chambers, cable alley, cable				
	glands plate etc. as required, duly painted from inside as well outside.				
	It shall have the following:				
	MAIN PANEL:				
	1 No.100 Amp. TPN, MCCB (25 KA breaking capacity),				
	Bus bars 100 Amp., 3 phase, 4 strips, 415 volts, 50 Hz. copper busbars with				
	colour coded PVC heat shrinkable sleeves. There should be 2 sets of BUS				
	BAR in such a way that AC load should not be connected to				
	GENERATOR power.				
	100 Amp. Changeover Switch				
	Instruments: Digital Multi function Meter of standard make for displaying				
	Input Voltage, Ampere, Power factor, KWH used with CTs.				
	OUTGOING:	Inte	rnal		
	5 Nos. 40 Amp. TP MCB (For LDB, PDB, Branch UPS, Inverter and Spare				
	Feeder) from Generator Powered Bus.				
	2 Nos. 63 Amp. TP, MCB (For AC DB and Spare Feeders) from Non-				
	Generator Powered Bus.				
	6-32 AMP DP MCB. 3 Nos (for Glow Sign board, Strong Room, and spare				
	feeder) from Generator Powered Bus.				
	The design of panel should be got approved by the Architect before				
	manufacturing. Also, the provision for 1/2 spare outgoings should be				
	considered for future expansion. The job shall be completed to the				
	satisfaction of the Bank.				
3	UPS I/P, O/P AND DISTRIBUTION & INVERTER INPUT & DISTRIBUTION				
a.	SITC of 32/40 Amp. TP MCB in Double Door enclosure complete (Branch	3.00	Nos.		
	and Inverter Incomers) complete in all respects as required.				
b.	SITC of 20/32 AMP Modular plug & socket along with MCB & plug top		Nos.		
	complete as per requirement and satisfaction of Bank. (2 for Branch's UPS				
	Input, 2 for Branch's UPS Output)				
c.	SITC of 8 WAY SPN Double Door DB complete with 1 No. 40 AMP DP MCB		No.		
	as incomer and 6 NOS. 6-10 AMP SPMCB as outgoing for Branch UPS				
	power distribution to Computer points on Staff Counters/ Tables.				
d.	SITC of 8 WAY SPN Double Door DB complete with 1 No. 32 AMP DP MCB		No.		
	as incomer and 6 NOS. 6-10 AMP SPMCB as outgoing for UPS power				
	distribution points for ESSENTIAL LOADS like CCTV System, Fire &				
	Burglar Alarm Systems, Networking Rack, ATM and select Light points				
	powered by UPS.				

Page 1 of 5 Seal-Sign of Tenderer



	Premises & Estate Section, Karnal Circle Office, Karnal					
	BOQ FOR ELECTRICAL WORKS AT: SECTOR 55 BRANCH, CAN					
S. NO.	DESCRIPTION OF ITEM	QTY		AMOUNT (Rs.)		
				(Excl. GST)	(Excl. GST)	
e.	SITC of 40/63 Amp. Rotary Phase selector switch complete with RYB	2.00	No			
	indication in enclosure for Branch's UPS input power network and Inverter.					
	Complete in all respect as required.					
f.	SITC of 4 WAY SPN Double Door DB complete with 1 No. 32 AMP DP MCB	1.00	No.			
-•	as incomer and 6 NOS. 6-10 AMP SPMCB as outgoing for UPS power	1.00	110.			
	distribution points for ESSENTIAL LOADS like CCTV System, Fire &					
	Burglar Alarm Systems, Networking Rack, ATM and select Light points					
	powered by UPS.					
5	RAW POWER & FAN, LIGHTING DB & AC DISTRIBUTION BOARD					
	•	1.00	Naa			
a.	SITC of 4 WAY HTPN DB IP43, IK 09, complete with 1 No. 40 AMP TP MCB		Nos.			
	as incomer and 12 NOS. 6-32 AMP. SPMCB for out going as PDB & AC DB					
_	complete in all respect as required.					
b.	SITC of 4 WAY HTPN DB IP43, IK 09, complete with 1 No. 63 AMP TP MCB	2.00	Nos.			
	as incomer and 12 NOS. 6-32 AMP. SPMCB for out going as PDB & AC DB					
	complete in all respect as required.					
6	CABLES					
	All cables/ wires shall be routed through PVC conduits/ bends/ elbows					
	etc., as required, of appropriate dia. The conduits shall be clamped					
	firmly to the walls/ columns/ pillars etc. with clips/ clamps and					
	fasteners rigidly even if above false ceiling.					
	Complete job shall include cutting chiseling in walls, floor and making					
	good of all chases/ cuts etc. with combination of cement-mortar,					
	including painiting with type and shade of existing wall. The work shall					
	be completed to the satisfaction of Bank.					
	NO CABLE/ WIRE/ CONDUIT SHALL BE VISIBLE IN THE BRANCH HALL/					
	CUSTOMER LOBBY/ STAFF WORKING AREA.					
а.	SITC of 3.5 Core 50.0 Sq.mm Aluminium conductor Armoured Cable for	20.00	Mtr.			
	service line connection up to Kit kat fuse unit complete in all respect as					
	required.					
b.	SITC of 4 core 6.0 Sq.mm Copper conductor Unarmoured Cable from main	40.00	Mtr.			
	Panel to					
	(a) LDB					
	(b) PDB					
	(c) Branch UPS input power supply.					
	Note: In case inverter is present at the branch, the wiring from LDB should					
	be with 2 X 6.0 +1 X 2.5 Sq.mm wiring mentioned below and not with 4					
	core 6.0 Sq.mm Cable					
c.	SITC of 2 runs of 6.0 Sq.mm and 1 no. of 2.5 Sq.mm FRLS PVC Insulated	60.00	Mtr.			
	Multistrand Copper conductor wire from selector switch to UPS to UPS					
	Distribution boards					
d.	SITC of 4 core 10.0 Sq.mm Copper conductor Unarmoured Cable from main	20.00	Mtr.			
	Panel/ Non Generator power Bus to					
	(a) AC DB					
1	(b) Inverter					

Page 2 of 5 Seal-Sign of Tenderer



	BOQ FOR ELECTRICAL WORKS AT: SECTOR 55 BRANCH, CAN	BOQ FOR ELECTRICAL WORKS AT: SECTOR 55 BRANCH, CANARA BANK AT O				
S. NO.	DESCRIPTION OF ITEM	QTY	ИОМ	RATE (Rs.) (Excl. GST)	AMOUNT (Rs.) (Excl. GST)	
e.	SITC of Sub main Wiring for Strong room and Glow Sign Board with 2 No. 4.0 Sq.mm and 1 No. 2.5 Sq.mm Multistrand Copper conductor FR pvc/ xlpe insulated Wire in required dia pvc conduit complete in all respects as required.	40.00	Mtr.			
f.	SITC of 2 runs of 10.0 Sq.mm and 1 no. of 2.5 Sq.mm FRLS PVC Insulated Multistrand Copper conductor wire from selector switch to inverter.	5.00	Mtr.			
7	AC (Split and Cassette) POINT					
a.	SITC of AC Point Wiring with 2 No. 4.0 Sq.mm and 1 No. 2.5 Sq.mm Multistrand Copper Wire & Modular plug & Socket with 10/16 Amp. SPMCB complete in all respect as required by the Bank (for 1.0/ 1.5 Tr Hi-Wall Split ACs)	3.00	Nos.			
b.	SITC of AC Point Wiring with 2 No. 6.0 Sq.mm and 1 No. 2.5 Sq.mm Multistrand Copper Wire & Modular plug & Socket with 20 Amp. SPMCB complete in all respect as required by the Bank (for 2.0 Tr Hi-Wall Split / Cassette ACs)	2.00	Nos.			
8	EARTHING					
a.	Preparation and commissioning of earth pits with PIP technology GEL type 50 mm dia 3000 mm long earth electrod. (One Dedicated Earthing for ATM UPS, Branch UPS and main panel)	4.00	Nos.			
b.	SITC of Earthing conductor from earth terminal to load point with 6.0 sq mm multstrand copper conductor FR pvc/ XLPE insulated cable in required dia pvc conduit complete in all respect as required.	60.00	Mtr.			
9	UPS POINT	12.00	Nos.			
	Supply & Installation of point wiring for UPS or stabilized power plug points on workstations/ table for computers using 3 X 1.5 Sq.mm copper conductor multi starnd FR PVC sheathed flexible wire including PVC conduite laid floor raceways/conduit and taken upto table top using PVC rigid or flexible conduits run within wooden/metal partitions. Each point consisting of 1 No. Phase Indication light, 1 No. 16 A Switch, 3 Nos 6A, 5/6 pin sockets & wired together forming one point. The earth wire of green color only.					
10	RAW POWER POINT					
a.	Supply & Installation of point wiring for Raw power plug points on workstations/ table for computers using 3 X 4 Sq.mm copper conductor PVC sheathed flexible wire including PVC conduite raceways and taken upto table top using PVC rigid or flexible conduits run within wooden/metal partitions. Each point consisting of 1 nos of 16A, 6 pin sockets & 1 No. 16 A Switch wired together forming one point. The earth wire of green color only.		Nos.			

Page 3 of 5 Seal-Sign of Tenderer



	BOQ FOR ELECTRICAL WORKS AT: SECTOR 55 BRANCH, CANARA BANK AT GURUGRAM					
S. NO.	DESCRIPTION OF ITEM	QTY	ИОМ	RATE (Rs.) (Excl. GST)	AMOUNT (Rs.) (Excl. GST)	
b.	Supply & Installation of point wiring for Raw power plug points on workstations/ table for computers using 3 X 2.5 Sq.mm copper conductor PVC sheathed flexible wire including PVC conduite raceways and taken upto table top using PVC rigid or flexible conduits run within wooden/metal partitions. Each point consisting of 1 Nos. 6A socket with switch, wired together forming one point. The earth wire of green color only.		Nos.			
11	LIGHT/ FAN POINT					
	Supply & Installation of concealed point wiring using 600 v grade 1.5 Sq.mm copper conductor PVC insulated wires (with proper R,Y,B color code) pulled through heavy gauge PVC conduits laid concealed over false ceiling including 2 Nos. 2.5 Sq.mm circuit wires from the relevant DB and also including 2.5 Sq.mm green color copper earth wire and switch plate, switches, etc. as approved by the Bank's Engineer/ Architect.					
а.	Primary light points including the cost of 6A modular switch	23.00	Nos.			
b.	Secondary light points looped from the above point	21.00	Nos.			
c.	Wall Fan Point along with 6 AMP switch	5.00	Nos.			
d.	Exhaust Fan Point along with 6 AMP switch	5.00	Nos.			
e.	Call Bell Point	1.00	Nos.			
	DATA CABLING & POINT Supplying and laying of D-Link make CAT-6 (UTP) cable through trenches / conduits. Supplying and laying D-link make CAT-6 Cable in P.V.C. Conduit Complete with CAT-6 information outlet with plate & suface Box at individual Tables	10.00	Nos.			
b.	Supplying and fixing of 1 mtr long crimped patch cord	10.00	Nos.			
<u>с.</u>	Supplying and fixing of 2 mtr long crimped patch cord	5.00	Nos.			
d.	Supplying and fixing of 9 U Rack complete with exhaust fan, lockable front glass door, cable managers, electrical socket board etc.	1.00	Nos.			
e.	Supplying and fixing of 24 port jack panel	1.00	Nos.			
13	VOICE NETWORKING		 			
a.	Supply and fixing of 2 nos. 10 pair telephone MDF consisting of tag blocks, disconnector type, complete with powder coated metal enclose, krone tag block mounting arrangement telephone distribution chart and locking arrangement [for P&T/ EPABX]	1.00	Job			
b.	Supplying and laying telephone cables 0.5 mm dia 2 pair electrolytic tinned copper conductors PVC insulated and twisted pair with rip cord, including PVC conduits/Racewaysand RJ11 telephone socket outlet. The rate shall include termination at both ends on tag blocks.					
(i)	2 Nos. RJ11 Telephone socket with plate and box	3.00	No.			
	FIXTURES	44.00				
a.	Supply and Installation of 36 W 2' X 2' Square LED light fitting of approved make	11.00	Nos.			

Page 4 of 5 Seal-Sign of Tenderer



S. NO.	DESCRIPTION OF ITEM	QTY	ИОМ	RATE (Rs.) (Excl. GST)	AMOUNT (Rs.) (Excl. GST)
b.	SITC of Tube Light - Patti Type (1 tube light to be provided for the under surface of the customer top of cash cabin)	11.00	Nos.		
c.	SITC of Down Lighter 18 W LED of approved make)	21.00	Nos.		
d.	SITC of LED Strip Light 15 W per 5 M with driver	2.00	Nos.		
е	SITC of 400 mm Metal Body Wall Mounted Fan (Crompton make)	5.00	Nos.		
f.	SITC of Exhaust Fan (9") (Crompton make) Metal Body	5.00	Nos.		
g.	SITC of Call Bell.	1.00	No.		
h.	Angle holder complete in all respect with 18 W CFL lamp (for Toilet)	2.00	Nos.		
(a)	BRANCH POWER INDICATOR LAMPS—for the three Circuits (Red, Blue & Yellow colour) for showing the power ON/off position for three circuits (i) Branch light (ii) AC/ Raw Power (iii) UPS output supply Supply installation Testing & commissioning of surface type Metal box made of sheet steel/ PVC and thickness not less that 2mm and structural steel/ PVC having light section completely dust tight and vermin proof and shall be painted with anti corrosive and anti condensation type two coats of primer and two coats of paint with front mounted pilot lamps for main		Each		
	supply, light DB, UPS DB & AC/Power DB.	50.00			
(b)	Supply Insatllation Testing and commissioning of 2x1.5sqmm 1100 V grade PVC insulated multi Stand FRLS copper conductor cable confirming IS694 thrugh 25mm dia PVC condiut on wall with saddle, interconnection, painting, making good to all damages etc. as required to be complete in all respect whrever required.	50.00	Mtrs.		

Page 5 of 5 Seal-Sign of Tenderer